

F2-IBT-200-20D

CFM	Static Pressure in Inches W.G.						
	0.000	0.500	1.000	1.500	2.000	2.500	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1300		834 / 0.30	1023 / 0.53	1184 / 0.79	1374 / 1.20		
1700		947 / 0.45	1139 / 0.76	1283 / 1.05	1410 / 1.37	1532 / 1.72	1663 / 2.16
2100	837 / 0.34	1063 / 0.66	1254 / 1.03	1401 / 1.41	1522 / 1.78	1629 / 2.15	1728 / 2.53
2500	996 / 0.58	1190 / 0.94	1366 / 1.37	1516 / 1.82	1639 / 2.27	1746 / 2.70	1842 / 3.14
2900	1155 / 0.90	1327 / 1.31	1482 / 1.77	1627 / 2.30	1754 / 2.83	1864 / 3.35	1961 / 3.85
3300	1314 / 1.32	1469 / 1.79	1607 / 2.29	1741 / 2.85	1865 / 3.45	1977 / 4.06	2077 / 4.65
3700	1474 / 1.86	1616 / 2.39	1735 / 2.91	1860 / 3.52	1979 / 4.17	2089 / 4.85	2189 / 5.52
4100	1633 / 2.54	1764 / 3.13	1876 / 3.70	1986 / 4.33	2095 / 5.01	2201 / 5.74	2301 / 6.49
4500	1791 / 3.35	1914 / 4.01	2016 / 4.62	2119 / 5.29	2219 / 6.00	2317 / 6.76	
4900	1951 / 4.33	2066 / 5.05	2162 / 5.72	2255 / 6.42	2348 / 7.16		

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00212ET3E184T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3H184T-W22 has an rpm range of 800 to 1150.
- Motor 00212OT3H184T-S has an rpm range of 800 to 1150.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor DHP0026 has an rpm range of 800 to 1150.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0026-50 has an rpm range of 800 to 958.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor EP0026 has an rpm range of 800 to 1150.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP0026 has an rpm range of 800 to 1150.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP0026 has an rpm range of 800 to 1150.
- Motor NP0034 has an rpm range of 800 to 1755.
- Motor NP0054 has an rpm range of 800 to 1745.