

F2-IBT-300-20D

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1200			1010 / 0.51	1199 / 0.81					
1600		842 / 0.32	1067 / 0.62	1255 / 0.99	1416 / 1.38	1556 / 1.79	1681 / 2.20		
2000		934 / 0.45	1137 / 0.78	1312 / 1.16	1470 / 1.60	1610 / 2.08	1738 / 2.57	1857 / 3.08	1965 / 3.59
2400		1034 / 0.63	1220 / 0.99	1382 / 1.39	1531 / 1.86	1667 / 2.36	1792 / 2.90	1911 / 3.48	2020 / 4.06
2800	913 / 0.45	1138 / 0.86	1313 / 1.26	1464 / 1.70	1603 / 2.18	1731 / 2.70	1852 / 3.26	1966 / 3.87	2074 / 4.50
3200	1044 / 0.68	1249 / 1.14	1412 / 1.60	1554 / 2.07	1684 / 2.58	1805 / 3.12	1920 / 3.70	2029 / 4.33	2133 / 4.98
3600	1173 / 0.96	1362 / 1.49	1516 / 2.00	1650 / 2.52	1773 / 3.06	1887 / 3.62	1996 / 4.23	2100 / 4.88	2199 / 5.55
4000	1304 / 1.32	1477 / 1.91	1622 / 2.48	1751 / 3.05	1867 / 3.63	1976 / 4.23	2080 / 4.87	2179 / 5.53	2274 / 6.22
4400	1435 / 1.76	1593 / 2.40	1732 / 3.04	1854 / 3.67	1966 / 4.29	2071 / 4.94	2169 / 5.60	2263 / 6.29	2354 / 7.00
4800	1565 / 2.28	1712 / 2.98	1843 / 3.69	1960 / 4.37	2068 / 5.05	2168 / 5.74	2263 / 6.44	2354 / 7.17	
5200	1695 / 2.90	1832 / 3.66	1956 / 4.42	2069 / 5.17	2172 / 5.91	2269 / 6.65	2360 / 7.40		
5600	1826 / 3.62	1953 / 4.44	2072 / 5.27	2179 / 6.07	2275 / 6.84				
6000	1956 / 4.45	2075 / 5.33	2187 / 6.21	2292 / 7.09					

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00212ET3E184T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3H184T-W22 has an rpm range of 800 to 1150.
- Motor 00212OT3H184T-S has an rpm range of 800 to 1150.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor DHP0026 has an rpm range of 800 to 1150.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0026-50 has an rpm range of 800 to 958.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor EP0026 has an rpm range of 800 to 1150.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP0026 has an rpm range of 800 to 1150.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP0026 has an rpm range of 800 to 1150.
- Motor NP0034 has an rpm range of 800 to 1755.
- Motor NP0054 has an rpm range of 800 to 1745.