

F2-IBT-800-400-400-20D

CFM	Static Pressure in Inches W.G.									
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
4000	1380 / 1.56	1463 / 1.86	1540 / 2.15	1611 / 2.43	1678 / 2.72	1741 / 3.00	1800 / 3.29	1858 / 3.58	1914 / 3.88	1968 / 4.19
4200	1449 / 1.81	1528 / 2.12	1602 / 2.43	1671 / 2.72	1736 / 3.02	1797 / 3.32	1856 / 3.62	1912 / 3.92	1966 / 4.23	2018 / 4.55
4400	1518 / 2.08	1594 / 2.41	1665 / 2.73	1732 / 3.04	1795 / 3.35	1855 / 3.67	1911 / 3.97	1966 / 4.29	2019 / 4.61	2071 / 4.94
4600	1587 / 2.38	1660 / 2.72	1729 / 3.05	1793 / 3.38	1855 / 3.71	1913 / 4.03	1968 / 4.36	2022 / 4.69	2074 / 5.02	2124 / 5.36
4800	1656 / 2.70	1726 / 3.06	1793 / 3.41	1855 / 3.75	1915 / 4.10	1972 / 4.44	2026 / 4.77	2079 / 5.12	2129 / 5.46	2178 / 5.81
5000	1725 / 3.05	1793 / 3.43	1857 / 3.79	1918 / 4.15	1976 / 4.51	2031 / 4.86	2084 / 5.22	2135 / 5.57	2184 / 5.92	2233 / 6.29
5200	1794 / 3.43	1858 / 3.82	1921 / 4.20	1980 / 4.58	2037 / 4.95	2091 / 5.32	2143 / 5.68	2192 / 6.05	2241 / 6.42	2289 / 6.80
5400	1862 / 3.84	1926 / 4.25	1986 / 4.65	2043 / 5.04	2099 / 5.43	2151 / 5.81	2201 / 6.18	2251 / 6.57	2299 / 6.96	2345 / 7.34
5600	1932 / 4.29	1992 / 4.71	2051 / 5.12	2107 / 5.53	2160 / 5.93	2211 / 6.32	2262 / 6.72	2309 / 7.12		

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00212ET3E184T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3H184T-W22 has an rpm range of 800 to 1150.
- Motor 00212OT3H184T-S has an rpm range of 800 to 1150.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor DHP0026 has an rpm range of 800 to 1150.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0026-50 has an rpm range of 800 to 958.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor EP0026 has an rpm range of 800 to 1150.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP0026 has an rpm range of 800 to 1150.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP0026 has an rpm range of 800 to 1150.
- Motor NP0034 has an rpm range of 800 to 1755.
- Motor NP0054 has an rpm range of 800 to 1745.