

F1-IBT-150-16Z

CFM	Static Pressure in Inches W.G.														
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
800	763 / 0.05	935 / 0.10	1093 / 0.16	1233 / 0.23	1361 / 0.30	1476 / 0.38	1587 / 0.46	1688 / 0.55	1786 / 0.64	1878 / 0.73	1956 / 0.81	2051 / 0.92	2133 / 1.02	2210 / 1.12	2286 / 1.22
1200	1144 / 0.18	1258 / 0.25	1373 / 0.32	1485 / 0.41	1589 / 0.50	1688 / 0.60	1783 / 0.70	1872 / 0.80	1958 / 0.91	2041 / 1.02	2120 / 1.14	2198 / 1.26	2273 / 1.38	2344 / 1.50	2414 / 1.62
1600	1525 / 0.42	1610 / 0.51	1697 / 0.61	1784 / 0.71	1869 / 0.82	1951 / 0.93	2033 / 1.05	2111 / 1.17	2186 / 1.30	2260 / 1.43	2329 / 1.56	2399 / 1.70	2465 / 1.83	2532 / 1.98	2597 / 2.13
2000	1907 / 0.82	1974 / 0.93	2043 / 1.05	2112 / 1.17	2183 / 1.30	2252 / 1.43	2320 / 1.56	2387 / 1.70	1905 / 0.82	2516 / 1.99	2581 / 2.14	2642 / 2.30	2703 / 2.46	2762 / 2.62	2821 / 2.78
2400	2288 / 1.43	2344 / 1.55	2400 / 1.69	2459 / 1.83	2516 / 1.97	2575 / 2.12	2632 / 2.27	2691 / 2.43	2746 / 2.59	2804 / 2.76	2861 / 2.93	2916 / 3.10	2970 / 3.28		

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 300 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 300 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 300 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 300 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 300 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 300 to 2770.