

F1-IBT-200-18Z

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1200	892 / 0.16	1020 / 0.24	1143 / 0.33	1257 / 0.42	1362 / 0.53	1458 / 0.63	1550 / 0.74	1637 / 0.86	1719 / 0.97	1796 / 1.09	1872 / 1.20	1945 / 1.32	2017 / 1.45	2083 / 1.57	2151 / 1.70	2214 / 1.82
1400	1041 / 0.25	1149 / 0.34	1259 / 0.44	1362 / 0.55	1458 / 0.66	1550 / 0.78	1636 / 0.90	1718 / 1.03	1795 / 1.16	1872 / 1.29	1942 / 1.42	2011 / 1.55	2080 / 1.69	2147 / 1.83	2208 / 1.97	2273 / 2.11
1600	1189 / 0.38	1284 / 0.48	1381 / 0.59	1475 / 0.71	1564 / 0.83	1648 / 0.96	1730 / 1.09	1808 / 1.23	1882 / 1.37	1954 / 1.52	2023 / 1.66	2089 / 1.81	2153 / 1.96	2216 / 2.11	2279 / 2.27	2336 / 2.42
1800	1337 / 0.53	1422 / 0.65	1508 / 0.77	1593 / 0.90	1674 / 1.03	1754 / 1.17	1831 / 1.32	1903 / 1.46	1974 / 1.62	2043 / 1.78	2108 / 1.93	2171 / 2.09	2236 / 2.26	2296 / 2.42	2353 / 2.59	2413 / 2.76
2000	1486 / 0.73	1561 / 0.86	1639 / 0.99	1717 / 1.13	1792 / 1.28	1866 / 1.43	1936 / 1.58	2006 / 1.74	2073 / 1.90	2139 / 2.07	2200 / 2.24	2262 / 2.41	2323 / 2.59	2381 / 2.77	2439 / 2.95	2494 / 3.13
2200	1634 / 0.98	1703 / 1.12	1773 / 1.26	1844 / 1.41	1913 / 1.56	1982 / 1.72	2048 / 1.89	2113 / 2.06	2178 / 2.23	2240 / 2.41	2299 / 2.59	2358 / 2.77	2415 / 2.96	2472 / 3.15	2526 / 3.34	2579 / 3.54
2400	1783 / 1.27	1846 / 1.42	1909 / 1.57	1974 / 1.73	2039 / 1.90	2102 / 2.07	2166 / 2.25	2226 / 2.43	2286 / 2.61	2346 / 2.80	2402 / 2.99	2459 / 3.18	2513 / 3.38	2567 / 3.58	2620 / 3.79	2673 / 4.00
2600	1932 / 1.61	1989 / 1.78	2049 / 1.94	2109 / 2.12	2167 / 2.29	2226 / 2.47	2285 / 2.66	2342 / 2.84	2401 / 3.04	2455 / 3.24	2510 / 3.44	2564 / 3.65	2616 / 3.85	2669 / 4.07	2720 / 4.28	2769 / 4.50

Max Sizeable RPM = 2900 RPM. Table shown extended beyond this point for reference only.

Motor 186726/A01-ECM-50-277-18 has an rpm range of 320 to 1950.

Motor 186726/A01-ECM-60-277-18 has an rpm range of 320 to 1950.

Motor 186730/A01-ECM-50-240-18 has an rpm range of 320 to 2700.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 320 to 2700.

Motor 186731/A01-ECM-50-480-18 has an rpm range of 320 to 2900.

Motor 186731/A01-ECM-60-480-18 has an rpm range of 320 to 2900.