

F1-IBT-400-200-200-15D

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
800		978 / 0.14	1180 / 0.24	1349 / 0.35	1495 / 0.46	1626 / 0.58	1747 / 0.71	1856 / 0.84	1961 / 0.98	2062 / 1.12	2156 / 1.27	2241 / 1.42	2332 / 1.59
1000	907 / 0.13	1116 / 0.22	1299 / 0.33	1458 / 0.46	1597 / 0.59	1724 / 0.73	1842 / 0.87	1949 / 1.02	2053 / 1.17	2146 / 1.32	2237 / 1.48	2326 / 1.65	2410 / 1.82
1200	1088 / 0.22	1267 / 0.33	1429 / 0.45	1575 / 0.59	1709 / 0.74	1832 / 0.90	1945 / 1.06	2051 / 1.23	2151 / 1.40	2243 / 1.57	2335 / 1.75	2419 / 1.93	2500 / 2.11
1400	1269 / 0.35	1424 / 0.47	1570 / 0.61	1703 / 0.76	1828 / 0.93	1944 / 1.10	2053 / 1.28	2154 / 1.46	2251 / 1.65	2345 / 1.84	2431 / 2.03	2518 / 2.24	2597 / 2.44
1600	1451 / 0.52	1587 / 0.66	1717 / 0.81	1839 / 0.98	1956 / 1.16	2065 / 1.34	2168 / 1.53	2263 / 1.73	2360 / 1.94	2450 / 2.15	2536 / 2.36	2619 / 2.58	2698 / 2.80
1800	1632 / 0.73	1754 / 0.90	1871 / 1.06	1985 / 1.25	2091 / 1.43	2195 / 1.64	2293 / 1.84	2387 / 2.06	2476 / 2.28	2564 / 2.51	2647 / 2.74	2727 / 2.97	
2000	1812 / 1.01	1923 / 1.18	2030 / 1.37	2134 / 1.57	2232 / 1.77	2328 / 1.98	2421 / 2.20	2513 / 2.43	2597 / 2.67	2681 / 2.91			
2200	1993 / 1.34	2095 / 1.54	2193 / 1.74	2289 / 1.95	2381 / 2.16	2472 / 2.39	2558 / 2.62	2644 / 2.87					
2400	2174 / 1.74	2268 / 1.95	2358 / 2.17	2446 / 2.39	2534 / 2.63	2617 / 2.87							
2600	2355 / 2.21	2441 / 2.44	2527 / 2.68	2608 / 2.91									

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

- Motor .5018OT3E56-S48PP has an rpm range of 800 to 1730.
- Motor .5018OT3E56-S48PP-50HZ has an rpm range of 800 to 1400.
- Motor .7518OT3E56-S48PP has an rpm range of 800 to 1735.
- Motor .7518OT3E56-S48PP-50Hz has an rpm range of 800 to 1410.
- Motor 00118ET3H143T-W22 has an rpm range of 800 to 1750.
- Motor 00118OT3H143T-S has an rpm range of 800 to 1750.
- Motor 00158ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00336OT3H145T-S has an rpm range of 900 to 3000.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN48-750I1-E-50-115 has an rpm range of 800 to 1800.
- Motor BMN48-750I1-E-60-115 has an rpm range of 800 to 1800.
- Motor BMN48-750I2-E-50-230/277 has an rpm range of 800 to 1800.
- Motor BMN48-750I2-E-60-230/277 has an rpm range of 800 to 1800.
- Motor DTP0014 has an rpm range of 800 to 1750.
- Motor DTP0014-50HZ has an rpm range of 800 to 1429.
- Motor DTP0016 has an rpm range of 800 to 1150.
- Motor DTP0022 has an rpm range of 900 to 3000.
- Motor DTP0022-50 has an rpm range of 900 to 3000.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0032 has an rpm range of 900 to 3000.
- Motor DTP1/54 has an rpm range of 800 to 1750.
- Motor DTP1/54-50HZ has an rpm range of 800 to 1426.
- Motor GP0014 has an rpm range of 800 to 1800.
- Motor GP0014-50 has an rpm range of 800 to 1440.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP1/54 has an rpm range of 800 to 1800.
- Motor GP1/54-50 has an rpm range of 800 to 1440.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP1/54 has an rpm range of 800 to 1730.