

F1-IBT-400-200-200-16Z

CFM	Static Pressure in Inches W.G.														
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
800	781 / 0.06	950 / 0.11	1107 / 0.17	1246 / 0.24	1372 / 0.31	1487 / 0.39	1597 / 0.47	1699 / 0.56	1794 / 0.65	1887 / 0.74	1975 / 0.83	2057 / 0.93	2139 / 1.03	2216 / 1.13	2292 / 1.23
1200	1171 / 0.19	1283 / 0.26	1397 / 0.34	1508 / 0.43	1611 / 0.52	1709 / 0.62	1802 / 0.72	1890 / 0.82	1977 / 0.93	2058 / 1.05	2135 / 1.16	2214 / 1.28	2286 / 1.40	2358 / 1.52	2429 / 1.65
1600	1561 / 0.46	1644 / 0.55	1730 / 0.64	1816 / 0.75	1900 / 0.86	1983 / 0.97	2062 / 1.09	2139 / 1.22	2213 / 1.34	2286 / 1.48	2356 / 1.61	2424 / 1.75	2492 / 1.89	2556 / 2.03	2619 / 2.17
2000	1951 / 0.89	2018 / 1.00	2086 / 1.12	2155 / 1.25	2222 / 1.37	2291 / 1.50	2358 / 1.64	2424 / 1.78	2491 / 1.93	2554 / 2.08	2618 / 2.24	2677 / 2.39	2736 / 2.54	2797 / 2.71	2853 / 2.87
2400	2341 / 1.54	2395 / 1.67	2451 / 1.81	2510 / 1.96	2567 / 2.10	2623 / 2.25	2682 / 2.41	2740 / 2.57	2794 / 2.73	2850 / 2.90	2906 / 3.07	2959 / 3.24			

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 300 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 300 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 300 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 300 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 300 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 300 to 2770.