

F2-IBT-400-200-200-20Z

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2000	956 / 0.33	1045 / 0.45	1129 / 0.58	1209 / 0.71	1286 / 0.85	1361 / 1.00	1434 / 1.14	1504 / 1.30	1571 / 1.45	1637 / 1.61	1701 / 1.78	1762 / 1.94	1823 / 2.12
2250	1076 / 0.47	1155 / 0.60	1231 / 0.74	1304 / 0.89	1374 / 1.04	1443 / 1.20	1510 / 1.36	1575 / 1.53	1639 / 1.70	1701 / 1.87	1761 / 2.05	1819 / 2.23	1877 / 2.41
2500	1195 / 0.64	1267 / 0.79	1336 / 0.94	1403 / 1.11	1467 / 1.27	1531 / 1.44	1592 / 1.62	1653 / 1.80	1712 / 1.98	1771 / 2.16	1827 / 2.35	1883 / 2.54	1938 / 2.74
2750	1315 / 0.85	1381 / 1.02	1444 / 1.18	1505 / 1.36	1565 / 1.54	1623 / 1.72	1681 / 1.91	1737 / 2.10	1793 / 2.30	1847 / 2.49	1900 / 2.70	1953 / 2.90	2004 / 3.11
3000	1434 / 1.11	1495 / 1.28	1553 / 1.47	1609 / 1.65	1666 / 1.85	1720 / 2.04	1774 / 2.25	1826 / 2.45	1879 / 2.66	1929 / 2.87	1980 / 3.09	2030 / 3.30	2079 / 3.53
3250	1554 / 1.41	1610 / 1.60	1664 / 1.80	1717 / 2.00	1769 / 2.20	1820 / 2.41	1870 / 2.63	1920 / 2.85	1969 / 3.07	2016 / 3.29	2063 / 3.52	2110 / 3.75	2157 / 3.98
3500	1673 / 1.76	1725 / 1.96	1776 / 2.17	1826 / 2.39	1875 / 2.61	1922 / 2.83	1970 / 3.06	2016 / 3.29	2061 / 3.52	2107 / 3.76	2153 / 4.01	2196 / 4.24	2241 / 4.50
3750	1793 / 2.17	1841 / 2.38	1889 / 2.61	1935 / 2.83	1981 / 3.07	2026 / 3.30	2071 / 3.54	2115 / 3.79	2158 / 4.03	2201 / 4.29	2244 / 4.55	2285 / 4.80	
4000	1912 / 2.63	1958 / 2.86	2003 / 3.10	2046 / 3.34	2090 / 3.59	2132 / 3.83	2174 / 4.09	2216 / 4.35	2257 / 4.61	2298 / 4.87			
4250	2032 / 3.15	2074 / 3.40	2117 / 3.65	2155 / 3.88	2200 / 4.17	2240 / 4.43	2280 / 4.70						
4500	2151 / 3.74	2192 / 4.00	2232 / 4.27	2272 / 4.54									
4750	2271 / 4.40												

Max Sizeable RPM = 2300 RPM. Table shown extended beyond this point for reference only.

Motor 186735/A01-ECM-50-240-20 has an rpm range of 300 to 2300.

Motor 186735/A01-ECM-60-240-20 has an rpm range of 300 to 2300.

Motor 186741/A01-ECM-50-480-20 has an rpm range of 300 to 2300.

Motor 186741/A01-ECM-60-480-20 has an rpm range of 300 to 2300.