

F2-IBT-400-200-200-22Z

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2000	768 / 0.33	863 / 0.46	958 / 0.61	1048 / 0.78	1132 / 0.95	1211 / 1.14	1284 / 1.32	1354 / 1.52	1420 / 1.72	1485 / 1.93	1546 / 2.13	1605 / 2.35	1663 / 2.57
2400	921 / 0.57	1000 / 0.71	1081 / 0.89	1159 / 1.08	1235 / 1.27	1306 / 1.48	1375 / 1.70	1440 / 1.92	1502 / 2.14	1562 / 2.37	1621 / 2.61	1676 / 2.84	1730 / 3.09
2800	1075 / 0.90	1141 / 1.07	1211 / 1.26	1280 / 1.47	1347 / 1.69	1412 / 1.92	1475 / 2.16	1536 / 2.40	1595 / 2.65	1651 / 2.91	1705 / 3.17	1759 / 3.43	1810 / 3.70
3200	1228 / 1.34	1286 / 1.53	1346 / 1.74	1407 / 1.97	1467 / 2.21	1527 / 2.47	1584 / 2.73	1640 / 2.99	1695 / 3.27	1748 / 3.55	1799 / 3.83	1850 / 4.12	
3600	1382 / 1.91	1433 / 2.12	1486 / 2.35	1540 / 2.59	1594 / 2.86	1648 / 3.13	1701 / 3.42	1752 / 3.70	1803 / 4.00	1852 / 4.30			
4000	1536 / 2.62	1582 / 2.85	1629 / 3.10	1677 / 3.37	1726 / 3.65	1774 / 3.94	1822 / 4.24						
4400	1689 / 3.48	1731 / 3.74	1773 / 4.01	1817 / 4.29	1861 / 4.59								

Max Sizeable RPM = 1870 RPM. Table shown extended beyond this point for reference only.

Motor 186729/A01-ECM-50-480-22 has an rpm range of 300 to 1870.

Motor 186729/A01-ECM-60-480-22 has an rpm range of 300 to 1870.

Motor 186732/A01-ECM-50-240-22 has an rpm range of 300 to 1870.

Motor 186732/A01-ECM-60-240-22 has an rpm range of 300 to 1870.