

F2-IBT-400-20Z

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2500	1010 / 0.34	1092 / 0.46	1169 / 0.59	1243 / 0.74	1313 / 0.89	1381 / 1.05	1448 / 1.22	1512 / 1.39	1575 / 1.56	1636 / 1.74	1696 / 1.92	1754 / 2.11	1812 / 2.30
3000	1212 / 0.59	1281 / 0.72	1346 / 0.88	1410 / 1.04	1471 / 1.22	1531 / 1.40	1590 / 1.59	1647 / 1.78	1703 / 1.98	1756 / 2.18	1811 / 2.38	1863 / 2.59	1914 / 2.80
3500	1414 / 0.93	1473 / 1.09	1530 / 1.26	1587 / 1.45	1640 / 1.64	1693 / 1.84	1738 / 2.02	1796 / 2.27	1846 / 2.49	1895 / 2.71	1943 / 2.94	1991 / 3.17	2038 / 3.40
4000	1616 / 1.39	1668 / 1.57	1719 / 1.76	1768 / 1.96	1817 / 2.18	1865 / 2.40	1911 / 2.63	1957 / 2.86	2002 / 3.10	2046 / 3.35	2090 / 3.60	2133 / 3.85	2176 / 4.11
4500	1817 / 1.98	1864 / 2.18	1910 / 2.39	1955 / 2.61	1998 / 2.84	2042 / 3.09	2083 / 3.33	2126 / 3.59	2167 / 3.85	2207 / 4.11	2248 / 4.39	2287 / 4.66	
5000	2019 / 2.71	2062 / 2.93	2103 / 3.16	2143 / 3.40	2183 / 3.66	2223 / 3.92	2261 / 4.19	2300 / 4.46					
5500	2221 / 3.61	2260 / 3.85	2297 / 4.10										

Max Sizeable RPM = 2300 RPM. Table shown extended beyond this point for reference only.

Motor 186735/A01-ECM-50-240-20 has an rpm range of 300 to 2300.

Motor 186735/A01-ECM-60-240-20 has an rpm range of 300 to 2300.

Motor 186741/A01-ECM-50-480-20 has an rpm range of 300 to 2300.

Motor 186741/A01-ECM-60-480-20 has an rpm range of 300 to 2300.