

F2-IBT-600-300-300-20D

CFM	Static Pressure in Inches W.G.														
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2500	863 / 0.38	988 / 0.56	1092 / 0.74	1185 / 0.92	1270 / 1.12	1351 / 1.32	1427 / 1.54	1500 / 1.77	1570 / 2.01	1638 / 2.26	1703 / 2.52	1766 / 2.79	1827 / 3.07	1885 / 3.35	1943 / 3.64
3000	1035 / 0.66	1143 / 0.88	1237 / 1.09	1320 / 1.31	1398 / 1.52	1471 / 1.75	1541 / 1.99	1608 / 2.23	1672 / 2.49	1734 / 2.76	1795 / 3.04	1854 / 3.32	1912 / 3.62	1967 / 3.92	2022 / 4.23
3500	1208 / 1.05	1302 / 1.31	1386 / 1.56	1463 / 1.80	1535 / 2.05	1603 / 2.31	1667 / 2.57	1728 / 2.83	1788 / 3.11	1846 / 3.40	1902 / 3.69	1956 / 3.99	2010 / 4.30	2062 / 4.62	2114 / 4.94
4000	1380 / 1.56	1463 / 1.86	1540 / 2.15	1611 / 2.43	1678 / 2.72	1741 / 3.00	1800 / 3.29	1858 / 3.58	1914 / 3.88	1968 / 4.19	2020 / 4.50	2071 / 4.82	2122 / 5.15	2170 / 5.48	2216 / 5.81
4500	1553 / 2.23	1626 / 2.55	1697 / 2.89	1763 / 3.21	1825 / 3.53	1884 / 3.85	1940 / 4.17	1994 / 4.49	2045 / 4.80	2097 / 5.14	2147 / 5.48	2195 / 5.83	2242 / 6.17	2289 / 6.53	2334 / 6.89
5000	1725 / 3.05	1793 / 3.43	1857 / 3.79	1918 / 4.15	1976 / 4.51	2031 / 4.86	2084 / 5.22	2135 / 5.57	2184 / 5.92	2233 / 6.29	2280 / 6.65	2326 / 7.02	2370 / 7.39		
5500	1897 / 4.06	1959 / 4.48	2018 / 4.88	2075 / 5.28	2129 / 5.67	2182 / 6.06	2232 / 6.46	2280 / 6.84	2328 / 7.23						

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00212ET3E184T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3H184T-W22 has an rpm range of 800 to 1150.
- Motor 00212OT3H184T-S has an rpm range of 800 to 1150.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor DHP0026 has an rpm range of 800 to 1150.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0026-50 has an rpm range of 800 to 958.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor EP0026 has an rpm range of 800 to 1150.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP0026 has an rpm range of 800 to 1150.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP0026 has an rpm range of 800 to 1150.
- Motor NP0034 has an rpm range of 800 to 1755.
- Motor NP0054 has an rpm range of 800 to 1745.