

F2-IBT-600-300-300-22Z

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2500	785 / 0.33	874 / 0.48	957 / 0.64	1037 / 0.80	1114 / 0.98	1188 / 1.16	1259 / 1.36	1327 / 1.57	1393 / 1.79	1457 / 2.02	1518 / 2.25	1577 / 2.48	1635 / 2.73
3000	942 / 0.57	1017 / 0.75	1089 / 0.94	1157 / 1.12	1224 / 1.32	1289 / 1.52	1352 / 1.74	1413 / 1.96	1473 / 2.20	1531 / 2.44	1588 / 2.70	1644 / 2.96	1698 / 3.22
3500	1099 / 0.90	1164 / 1.12	1226 / 1.33	1286 / 1.55	1345 / 1.76	1403 / 1.99	1459 / 2.22	1514 / 2.47	1568 / 2.72	1621 / 2.98	1673 / 3.25	1724 / 3.52	1774 / 3.81
4000	1256 / 1.34	1313 / 1.60	1368 / 1.84	1422 / 2.09	1474 / 2.33	1526 / 2.58	1577 / 2.83	1627 / 3.10	1676 / 3.37	1724 / 3.64	1771 / 3.93	1818 / 4.22	1864 / 4.52
4500	1413 / 1.91	1464 / 2.20	1513 / 2.48	1561 / 2.75	1609 / 3.02	1656 / 3.30	1702 / 3.58	1747 / 3.86	1792 / 4.15	1836 / 4.45			
5000	1570 / 2.62	1616 / 2.94	1661 / 3.25	1704 / 3.56	1748 / 3.86	1791 / 4.17	1833 / 4.47						
5500	1727 / 3.49	1768 / 3.84	1810 / 4.19	1849 / 4.52									

Max Sizeable RPM = 1870 RPM. Table shown extended beyond this point for reference only.

Motor 186729/A01-ECM-50-480-22 has an rpm range of 300 to 1870.

Motor 186729/A01-ECM-60-480-22 has an rpm range of 300 to 1870.

Motor 186732/A01-ECM-50-240-22 has an rpm range of 300 to 1870.

Motor 186732/A01-ECM-60-240-22 has an rpm range of 300 to 1870.