

## F2-IBT-800-400-400-20Z

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
4000	1645 / 1.50	1704 / 1.71	1759 / 1.93	1810 / 2.15	1859 / 2.37	1906 / 2.60	1952 / 2.83	1998 / 3.08	2042 / 3.32	2086 / 3.57	2128 / 3.81	2168 / 4.06	2212 / 4.33
4200	1728 / 1.74	1784 / 1.96	1836 / 2.18	1886 / 2.41	1933 / 2.65	1979 / 2.89	2023 / 3.13	2067 / 3.38	2109 / 3.63	2152 / 3.89	2193 / 4.15	2233 / 4.41	2274 / 4.68
4400	1810 / 2.00	1864 / 2.23	1915 / 2.46	1963 / 2.70	2008 / 2.95	2052 / 3.20	2095 / 3.45	2137 / 3.71	2178 / 3.97	2219 / 4.24	2259 / 4.50	2298 / 4.77	
4600	1892 / 2.29	1944 / 2.52	1993 / 2.77	2039 / 3.02	2083 / 3.27	2126 / 3.53	2168 / 3.80	2208 / 4.06	2248 / 4.33	2287 / 4.61			
4800	1974 / 2.60	2024 / 2.85	2072 / 3.10	2115 / 3.36	2158 / 3.62	2200 / 3.89	2241 / 4.17	2280 / 4.44					
5000	2057 / 2.94	2105 / 3.20	2151 / 3.46	2193 / 3.72	2235 / 4.00	2275 / 4.28							
5200	2139 / 3.30	2186 / 3.57	2229 / 3.84	2271 / 4.12									
5400	2220 / 3.69	2266 / 3.98											

Max Sizeable RPM = 2300 RPM. Table shown extended beyond this point for reference only.

Motor 186735/A01-ECM-50-240-20 has an rpm range of 300 to 2300.

Motor 186735/A01-ECM-60-240-20 has an rpm range of 300 to 2300.

Motor 186741/A01-ECM-50-480-20 has an rpm range of 300 to 2300.

Motor 186741/A01-ECM-60-480-20 has an rpm range of 300 to 2300.