

F2-IBT-800-400-400-22Z

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
4000	1256 / 1.34	1313 / 1.60	1368 / 1.84	1422 / 2.09	1474 / 2.33	1526 / 2.58	1577 / 2.83	1627 / 3.10	1676 / 3.37	1724 / 3.64	1771 / 3.93	1818 / 4.22	1864 / 4.52
4200	1319 / 1.56	1373 / 1.82	1426 / 2.08	1477 / 2.33	1527 / 2.59	1577 / 2.85	1626 / 3.11	1673 / 3.38	1721 / 3.66	1768 / 3.95	1813 / 4.24	1859 / 4.54	
4400	1381 / 1.79	1433 / 2.07	1484 / 2.34	1533 / 2.60	1582 / 2.87	1630 / 3.14	1676 / 3.42	1723 / 3.70	1768 / 3.98	1813 / 4.28	1857 / 4.58		
4600	1444 / 2.04	1494 / 2.34	1543 / 2.62	1590 / 2.90	1636 / 3.18	1683 / 3.46	1727 / 3.74	1772 / 4.03	1816 / 4.33	1859 / 4.63			
4800	1507 / 2.32	1555 / 2.63	1602 / 2.93	1647 / 3.22	1692 / 3.51	1736 / 3.80	1780 / 4.10	1823 / 4.40	1866 / 4.70				
5000	1570 / 2.62	1616 / 2.94	1661 / 3.25	1704 / 3.56	1748 / 3.86	1791 / 4.17	1833 / 4.47						
5200	1633 / 2.95	1677 / 3.28	1720 / 3.60	1763 / 3.93	1804 / 4.24	1845 / 4.56							
5400	1695 / 3.31	1738 / 3.65	1779 / 3.98	1821 / 4.32	1861 / 4.65								
5600	1758 / 3.69	1799 / 4.05	1840 / 4.40										
5800	1821 / 4.10	1861 / 4.47											

Max Sizeable RPM = 1870 RPM. Table shown extended beyond this point for reference only.

Motor 186729/A01-ECM-50-480-22 has an rpm range of 300 to 1870.

Motor 186729/A01-ECM-60-480-22 has an rpm range of 300 to 1870.

Motor 186732/A01-ECM-50-240-22 has an rpm range of 300 to 1870.

Motor 186732/A01-ECM-60-240-22 has an rpm range of 300 to 1870.