

# F3-IBT-1000-300-300-400-25Z

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
5500	1192 / 1.93	1232 / 2.20	1273 / 2.50	1316 / 2.81	1359 / 3.14	1402 / 3.49	1445 / 3.84	1488 / 4.21	1530 / 4.57	1571 / 4.95	1612 / 5.34	1652 / 5.73	1691 / 6.12
6000	1301 / 2.51	1336 / 2.80	1374 / 3.12	1413 / 3.45	1452 / 3.80	1492 / 4.17	1532 / 4.55	1572 / 4.93	1611 / 5.33	1649 / 5.73	1687 / 6.14	1725 / 6.55	1762 / 6.97
6500	1409 / 3.19	1442 / 3.51	1476 / 3.84	1512 / 4.20	1548 / 4.57	1585 / 4.96	1621 / 5.36	1658 / 5.76	1694 / 6.18	1731 / 6.60	1767 / 7.04		
7000	1517 / 3.99	1548 / 4.32	1579 / 4.68	1612 / 5.06	1646 / 5.45	1679 / 5.86	1713 / 6.28	1747 / 6.70	1781 / 7.14				
7500	1626 / 4.90	1654 / 5.26	1684 / 5.64	1714 / 6.04	1745 / 6.45	1776 / 6.88							
8000	1734 / 5.95	1761 / 6.33	1788 / 6.73										

Max Sizeable RPM = 1800 RPM. Table shown extended beyond this point for reference only.

Motor 186733/A01-ECM-50-480-25 has an rpm range of 300 to 1800.

Motor 186733/A01-ECM-60-480-25 has an rpm range of 300 to 1800.

Motor 186736/A01-ECM-50-480-25 has an rpm range of 300 to 1580.

Motor 186736/A01-ECM-60-480-25 has an rpm range of 300 to 1580.

Motor 186738/A01-ECM-50-240-25 has an rpm range of 300 to 1580.

Motor 186738/A01-ECM-60-240-25 has an rpm range of 300 to 1580.