

# F3-IBT-800-400-400-24D

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
3500		868 / 1.29	1004 / 1.89	1122 / 2.54	1227 / 3.22	1322 / 3.94	1410 / 4.68	1493 / 5.46	1570 / 6.25
4000		950 / 1.73	1078 / 2.40	1189 / 3.10	1290 / 3.85	1382 / 4.63	1468 / 5.44	1548 / 6.27	1623 / 7.13
4500	887 / 1.45	1035 / 2.26	1155 / 3.01	1261 / 3.78	1357 / 4.59	1446 / 5.43	1529 / 6.30	1607 / 7.20	1681 / 8.12
5000	985 / 1.99	1123 / 2.91	1235 / 3.74	1335 / 4.58	1427 / 5.45	1513 / 6.35	1593 / 7.28	1669 / 8.24	1741 / 9.22
5500	1084 / 2.65	1211 / 3.67	1318 / 4.60	1413 / 5.51	1501 / 6.45	1583 / 7.41	1661 / 8.40	1734 / 9.42	
6000	1182 / 3.44	1301 / 4.57	1402 / 5.59	1493 / 6.58	1577 / 7.59	1656 / 8.62	1731 / 9.67		
6500	1281 / 4.38	1392 / 5.62	1488 / 6.73	1575 / 7.81	1655 / 8.89	1731 / 9.99			
7000	1379 / 5.47	1484 / 6.82	1575 / 8.03	1658 / 9.19					
7500	1478 / 6.73	1577 / 8.19	1664 / 9.50						
8000	1576 / 8.16	1670 / 9.73							

Max Sizeable RPM = 2000 RPM. Table shown extended beyond this point for reference only.

- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00512ET3E215T-W22 has an rpm range of 800 to 1150.
- Motor 00512OT3H215T-S has an rpm range of 800 to 1150.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor 01018OT3H215T-S has an rpm range of 800 to 1750.
- Motor DHP0056 has an rpm range of 800 to 1165.
- Motor DP010504NPW01 has an rpm range of 800 to 1750.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP0104 has an rpm range of 800 to 1755.
- Motor DTP0104-50 has an rpm range of 800 to 1436.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor GP0056 has an rpm range of 800 to 1150.
- Motor GP0104 has an rpm range of 800 to 1755.
- Motor GP0104-50 has an rpm range of 800 to 1440.
- Motor NP0056 has an rpm range of 800 to 1150.