

FAWP-18

CFM	Static Pressure in Inches W.G.									
	0.000	0.125	0.250	0.375	0.500	0.625	0.750	0.875	1.000	1.125
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
200		467 / 0.03	647 / 0.07							
700		584 / 0.04	758 / 0.10	889 / 0.17	1000 / 0.25	1099 / 0.34	1188 / 0.43	1270 / 0.53	1349 / 0.64	1423 / 0.75
1200	444 / 0.01	681 / 0.06	872 / 0.13	1009 / 0.22	1123 / 0.32	1221 / 0.43	1309 / 0.54	1390 / 0.65		
1700	629 / 0.03	776 / 0.08	964 / 0.16	1113 / 0.27	1234 / 0.38	1338 / 0.51	1429 / 0.64			
2200	813 / 0.07	913 / 0.12	1053 / 0.19	1200 / 0.30	1328 / 0.43	1438 / 0.57	1535 / 0.72			
2700	998 / 0.14	1074 / 0.19	1173 / 0.26	1291 / 0.35	1413 / 0.48	1525 / 0.63				
3200	1182 / 0.23	1244 / 0.28	1319 / 0.35	1408 / 0.44	1508 / 0.56	1611 / 0.70				
3700	1367 / 0.35	1419 / 0.41	1479 / 0.49	1548 / 0.58	1627 / 0.69					
4200	1552 / 0.51	1596 / 0.58	1647 / 0.66							
4700	1736 / 0.72									

Max Sizeable RPM = 1800 RPM. Table shown extended beyond this point for reference only.

Motor BMN48-56011-50-115 has an rpm range of 300 to 1800.

Motor BMN48-56011-60-115 has an rpm range of 300 to 1800.

Motor BMN48-56012-50-230/277 has an rpm range of 300 to 1800.

Motor BMN48-56012-60-230/277 has an rpm range of 300 to 1800.

Motor CK48HF15FF01-50-115 has an rpm range of 1075 to 1360.

Motor CK48HF15FF01-50-230 has an rpm range of 1075 to 1400.

Motor CK48HF15FF01-60-115 has an rpm range of 1075 to 1625.

Motor CK48HF15FF01-60-230 has an rpm range of 1075 to 1625.