

# FAWPD-24-A

CFM	Static Pressure in Inches W.G.						
	0.000	0.250	0.500	0.750	1.000	1.250	1.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1000		664 / 0.13	884 / 0.35	1049 / 0.61	1188 / 0.92	1309 / 1.26	1418 / 1.63
2000	355 / 0.02	778 / 0.19	1009 / 0.43	1183 / 0.73	1328 / 1.08	1455 / 1.46	1567 / 1.87
3000	532 / 0.05	883 / 0.27	1118 / 0.55	1297 / 0.88	1446 / 1.26	1576 / 1.67	
4000	708 / 0.12	991 / 0.39	1224 / 0.71	1404 / 1.08	1555 / 1.49	1688 / 1.93	
5000	885 / 0.24	1110 / 0.55	1330 / 0.93	1509 / 1.34	1661 / 1.79		
6000	1061 / 0.41	1242 / 0.77	1441 / 1.20	1615 / 1.67			
7000	1238 / 0.65	1388 / 1.06	1560 / 1.54				
8000	1415 / 0.98	1543 / 1.42	1691 / 1.95				
9000	1592 / 1.39	1703 / 1.88					
10000	1768 / 1.90						

Max Sizeable RPM = 1800 RPM. Table shown extended beyond this point for reference only.

Motor 00112ET3H145T-W22 has an rpm range of 300 to 1150.

Motor 00112OT3H145T-S has an rpm range of 300 to 1150.

Motor 00158ET3H145T-W22 has an rpm range of 438 to 1750.

Motor 00158OT3H145T-S has an rpm range of 440 to 1750.

Motor 00218ET3H145T-W22 has an rpm range of 438 to 1750.

Motor 00218OT3H145T-S has an rpm range of 440 to 1750.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 360 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 360 to 1800.

Motor DTP0016 has an rpm range of 300 to 1150.

Motor DTP0016-50 has an rpm range of 300 to 958.

Motor DTP0024 has an rpm range of 435 to 1740.

Motor DTP0024-50HZ has an rpm range of 354 to 1415.

Motor DTP1/54 has an rpm range of 437 to 1750.

Motor DTP1/54-50HZ has an rpm range of 357 to 1426.

Motor GP0016 has an rpm range of 300 to 1150.

Motor GP0016-50 has an rpm range of 300 to 958.

Motor GP0024 has an rpm range of 450 to 1740.

Motor GP0024-50 has an rpm range of 360 to 1440.

Motor GP1/54 has an rpm range of 450 to 1800.

Motor GP1/54-50 has an rpm range of 360 to 1440.