

# FAWPD-30-S

CFM	Static Pressure in Inches W.G.									
	0.000	0.125	0.250	0.375	0.500	0.625	0.750	0.875	1.000	1.125
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2500		441 / 0.13	558 / 0.28	644 / 0.46	715 / 0.66	776 / 0.88	831 / 1.11	881 / 1.35	928 / 1.61	971 / 1.88
3500	338 / 0.04	502 / 0.17	622 / 0.36	713 / 0.56	787 / 0.79	851 / 1.04	909 / 1.30	960 / 1.57	1008 / 1.86	
4500	434 / 0.08	569 / 0.24	683 / 0.44	775 / 0.68	852 / 0.94	919 / 1.21	978 / 1.50	1032 / 1.80		
5500	530 / 0.15	644 / 0.32	746 / 0.55	835 / 0.81	913 / 1.10	981 / 1.40	1043 / 1.72			
6500	626 / 0.24	724 / 0.44	815 / 0.69	898 / 0.97	974 / 1.28	1042 / 1.61	1104 / 1.95			
7500	722 / 0.37	808 / 0.59	889 / 0.86	966 / 1.17	1037 / 1.50	1103 / 1.85				
8500	818 / 0.53	895 / 0.78	968 / 1.07	1037 / 1.40	1104 / 1.75					
9500	914 / 0.74	983 / 1.01	1049 / 1.33	1113 / 1.67						
10500	1010 / 1.00	1073 / 1.30	1134 / 1.63	1192 / 2.00						
11500	1107 / 1.32	1164 / 1.64	1220 / 1.99							
12500	1203 / 1.69									

Max Sizeable RPM = 1250 RPM. Table shown extended beyond this point for reference only.

Motor 00152ET3H182T-W22 has an rpm range of 300 to 1150.

Motor 00212ET3H184T-W22 has an rpm range of 300 to 1150.

Motor 00212OT3H184T-S has an rpm range of 300 to 1150.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 300 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 300 to 1200.

Motor DTP0026 has an rpm range of 300 to 1150.

Motor DTP0026-50 has an rpm range of 300 to 958.

Motor DTP1/56 has an rpm range of 300 to 1150.

Motor DTP1/56-50 has an rpm range of 300 to 958.

Motor GP0026 has an rpm range of 300 to 1150.

Motor GP1/56 has an rpm range of 300 to 1150.

Motor NP0026 has an rpm range of 300 to 1150.