

FAWPD-48-A

CFM	Static Pressure in Inches W.G.								
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
5000		356 / 0.52	472 / 1.34	560 / 2.33	633 / 3.44	697 / 4.68	754 / 6.01	807 / 7.43	857 / 8.93
11000		419 / 0.76	550 / 1.74	647 / 2.95	725 / 4.33	794 / 5.84	854 / 7.46	909 / 9.19	
17000	355 / 0.48	489 / 1.25	607 / 2.32	707 / 3.63	792 / 5.15	866 / 6.82	931 / 8.64		
23000	480 / 1.17	584 / 2.13	678 / 3.31	766 / 4.71	848 / 6.30	923 / 8.07	991 / 10.00		
29000	605 / 2.35	691 / 3.50	768 / 4.84	841 / 6.35	913 / 8.04	982 / 9.88			
35000	730 / 4.14	804 / 5.47	869 / 6.99	932 / 8.66					
41000	855 / 6.65	920 / 8.18	977 / 9.88						

Max Sizeable RPM = 1000 RPM. Table shown extended beyond this point for reference only.

Motor 00509ET3E254T-W22 has an rpm range of 300 to 880.

Motor 00509ET3E254T-W22-50 has an rpm range of 300 to 730.

Motor 00712ET3H254T-W22 has an rpm range of 300 to 1000.

Motor 00712OT3H254T-S has an rpm range of 300 to 1000.

Motor 01012ET3H256T-W22 has an rpm range of 300 to 1000.

Motor 01012OT3H256T-S has an rpm range of 300 to 1000.

Motor DTP0106 has an rpm range of 300 to 1000.

Motor DTP7/56 has an rpm range of 300 to 1000.

Motor DTP7/56-50 has an rpm range of 300 to 958.

Motor NP0056 has an rpm range of 300 to 1000.

Motor NP0106 has an rpm range of 300 to 1000.

Motor NP0106-50 has an rpm range of 300 to 958.