

FAWPD-48-S

CFM	Static Pressure in Inches W.G.				
	0.000	0.125	0.250	0.375	0.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
6000			361 / 0.61	410 / 0.93	450 / 1.29
8000		313 / 0.36	402 / 0.79	457 / 1.21	500 / 1.63
10000		338 / 0.44	429 / 0.94	495 / 1.48	544 / 2.00
12000		374 / 0.57	449 / 1.06	523 / 1.70	579 / 2.35
14000	346 / 0.35	416 / 0.76	475 / 1.22	543 / 1.87	606 / 2.63
16000	396 / 0.53	461 / 1.00	510 / 1.47	566 / 2.09	625 / 2.87
18000	445 / 0.75	507 / 1.30	550 / 1.80	596 / 2.39	647 / 3.13
20000	495 / 1.03	554 / 1.66	593 / 2.19	632 / 2.79	675 / 3.50
22000	544 / 1.37	601 / 2.10	637 / 2.67	673 / 3.29	710 / 3.99
24000	594 / 1.78	649 / 2.60	683 / 3.23	715 / 3.87	748 / 4.58
26000	643 / 2.27	697 / 3.19	730 / 3.87	760 / 4.55	789 / 5.28
28000	692 / 2.83	745 / 3.86	777 / 4.60		
30000	742 / 3.48	793 / 4.62			
32000	791 / 4.22				

Max Sizeable RPM = 800 RPM. Table shown extended beyond this point for reference only.

Motor 00509ET3E254T-W22 has an rpm range of 300 to 800.

Motor 00509ET3E254T-W22-50 has an rpm range of 300 to 730.

Motor 00712ET3H254T-W22 has an rpm range of 300 to 800.

Motor 00712OT3H254T-S has an rpm range of 300 to 800.

Motor DTP7/56 has an rpm range of 300 to 800.

Motor DTP7/56-50 has an rpm range of 300 to 800.

Motor NP7/56 has an rpm range of 300 to 800.

Motor NP7/56-50 has an rpm range of 300 to 800.