

SA16Z

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
500			916 / 0.09	1085 / 0.14	1232 / 0.20	1362 / 0.26	1484 / 0.33	1592 / 0.40	1701 / 0.47	1799 / 0.55	1887 / 0.62	1976 / 0.70	2066 / 0.79	2146 / 0.88	2222 / 0.96	2294 / 1.04
1000	897 / 0.08	1043 / 0.14	1181 / 0.21	1309 / 0.28	1427 / 0.36	1536 / 0.44	1642 / 0.54	1739 / 0.63	1832 / 0.73	1919 / 0.83	2000 / 0.92	2088 / 1.04	2169 / 1.15	2247 / 1.26	2320 / 1.38	2392 / 1.49
1500	1344 / 0.28	1442 / 0.36	1540 / 0.45	1636 / 0.54	1728 / 0.64	1816 / 0.75	1901 / 0.86	1984 / 0.97	2063 / 1.09	2140 / 1.21	2216 / 1.34	2287 / 1.47	2358 / 1.60	2427 / 1.74	2496 / 1.88	2560 / 2.02
2000	1792 / 0.67	1866 / 0.77	1940 / 0.88	2012 / 1.00	2086 / 1.12	2157 / 1.25	2227 / 1.38	2291 / 1.50	2361 / 1.64	2427 / 1.79	2494 / 1.94	2558 / 2.09	2618 / 2.24	2677 / 2.39	2740 / 2.56	2797 / 2.72
2500	2240 / 1.31	2298 / 1.44	2358 / 1.57	2415 / 1.71	2475 / 1.85	2533 / 1.99	2591 / 2.14	2648 / 2.30	2706 / 2.46	2762 / 2.62	2818 / 2.79	2874 / 2.96	2927 / 3.13	2980 / 3.31		
3000	2688 / 2.27	2737 / 2.42	2786 / 2.57	2836 / 2.74	2885 / 2.90	2933 / 3.06	2982 / 3.24									

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 800 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 800 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 800 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 800 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 800 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 800 to 2770.